OMNITRONIC LH071 DI-BOX STEREO



56,00 € tax included

Reference: OMLH071

OMNITRONIC LH071 DI-BOX STEREO

Dual DI box/splitter

Active 2-channel DI box with split mode
2 high-impedance signal inputs via combo connectors (XLR/6.3 mm jack)
2 low-impedance XLR outputs
Converts 2 separate unbalanced line inputs (e.g. instruments) into 2 balanced XLR outputs, for connecting a mixer
Switchable to split mode (input 1 routes the signal to both outputs)
Input sensitivity switchable: +20 dB, 0 dB, -30 dB
Ground-lift switch eliminates signal interference and ground loop problems
Phase can be switched
Hi-cut 10 kHz switchable
Modern convex housing design with rubber corners for safe positioning
Stackable
Cables can be routed under the housing
Operation with 9 V battery (included)

Power supply:9 V battery
Current consumption:approx. 65 mA
Battery life:6 - 8 hours
Frequency range:10 Hz - 30 kHz
Input impedance:470 kohms
Output impedance:600 ohms
Maximum output level:6 dBu
Dynamic range:>100 dB
Hi cut:10 kHz
Input connectors:2 x combo XLR/6.3 mm jack
Output connectors:2 x XLR, bal.
THD:0.5 %
Dimensions:150 x 130 x 60 mm
Weight:0.5 kg