

## KORG LCA 120

**99,00 € tax included**

Reference: KOLCA120

KORG LCA 120



### Korg LCA-120 Chromatic Flip-Up Digital Tuner Specifications:

Scale: 12 note equal temperament, program (88 notes)

Detection Range: A0 (27.50 Hz) to C8 (4186.01 Hz)

Reference Tone: C2 (65.41 Hz) to C6 (1046.50 Hz)

Tuning Modes: Meter (AUTO), Focus Tune (AUTO), Sound Out (MANUAL), Sound Back (AUTO)

Calibration Range: A4 = 410 Hz to 480 Hz (1 Hz step)

Detection Accuracy: Better than  $\pm 1.0$  cent

Sound Accuracy: Better than  $\pm 1.5$  cents

Volume Detection Display

Programmable Temperament Function

Connections: INPUT (1/4"), Headphones (1/8" mini), DC IN (9V)

Speaker: Dynamic speaker (16 mm x 35 mm)

Power Supply: Two AAA alkaline batteries (3V) or AC adapter

Battery Life: Approximately 60 hours (when tuner is operating with alkaline batteries, Meter mode, A4 continuous input and back-light off)

Dimensions: 3.98" (W) x 3.31" (D) x 0.81" (H) (folded)

Weight: 5.22 oz. (including batteries)

Included Items: Two AAA batteries for checking operation Korg LCA-120 Chromatic Flip-Up Digital Tuner Features:

Extra large backlit LCD for excellent visibility

"Focus Tune" function allows for even more accurate tuning within  $\pm 10$  cents

Sound Level meter visually indicates the volume of a performance

Korg's own Sound Back mode lets you tune using a reference tone together with the meter (using the optional CM-100L contact microphone)

Temperament Program function lets you specify the tuning pitch for each note

A wide tuning range of A0-C8 (88 notes) and adjustable calibration (410 Hz-480 Hz) supports all types of instruments

A four-octave reference tone is built-in

Indicator marks for perfect major and minor thirds are provided

Built-in microphone